

## Binding Receivers

Spektrum DX5e / AR600 recvr.

- 1) Insert bind plug in Bind/Data port
- 2) Plug battery in any port in receiver
  - a) LED is flashing and in Bind mode
  - b) Move throttle to desired Smartsafe position
- 3) Pull and hold trainer switch and turn on power
- 4) Release Trainer switch when Transmitter LEDs flash and a tone is heard
  - a) Within seconds the system should connect (Bind)
  - b) When connected, Receiver LED will go solid
- 5) Remove the Bind plug, you're done

Spektrum DX6i with Spektrum receiver

- 1) Transmitter power off and throttle in lowest position
- 2) Insert Bind plug in BIND port
- 3) Insert battery into any port
  - a) Receiver LED flashes when ready to bind
- 4) Pull and hold trainer switch and turn on power
- 5) Hold Trainer switch until Receiver LED stays lit, then release
- 6) Receiver is bound, remove bind plug

Spektrum Radio with Orange receiver

- 1) Insert a servo in appropriate port
- 2) Insert BIND plug in Batt/Bind port
- 3) Plug battery in any port
  - a) Rapid flashing orange LED = receiver in BIND mode
- 4) Hold trainer switch forward on turn on Radio
  - a) Receiver LED will go out then on solid
- 5) Release Trainer switch and turn Radio off
- 6) Remove battery from receiver
- 7) Remove BIND plug
- 8) Turn Radio on
- 9) Put battery in BATT/BIND port
- 10) Within seconds the Receiver will have solid orange LED
  - a) Receiver is now bound

Futaba 4YF-2.4GHz with R2004 Receiver

- 1) Place Radio within 1 meter of Receiver
- 2) Turn on Radio
- 3) Turn on Receiver
- 4) Push and hold the Link switch on the Receiver
- 5) When Link is complete, Receiver LED changes to solid green